



Installing the SIM card and battery

1. Remove the battery cover and insert the SIM card.




2. Install the battery and reattach the cover.





4 Charging the battery

1. Plug the supplied travel adapter.



2. When charging is finished, unplug the adapter.




: Do not remove the battery from the phone without unplugging the adapter first. Otherwise, the phone may be damaged.

W Phone layout and key functions



disables all sounds on the phone, when pressed and held in Idle mode. To exit, press and hold this key again

Your phone is in Idle mode when you are not on a call or using a menu. You must be in Idle mode to dial a phone number.



Your phone displays the following status indicators on the top of the

Received signal strength Tail

6 Call in progress

73 Out of your service area; you cannot make or receive calls.

G

R Roaming network

倡 Silent mode or the call ringer set to Vibration

X Mute mode

Call diverting feature active ϕ

 \Rightarrow IrDA feature active

 \bowtie New text message

•= New multimedia message

m New voicemail message

 \triangle Alarm set

Battery power level

Switching on or off the phone

- 1. Press and hold for more than one second to switch on the phone.
- 2. To switch off the phone, press and hold $\overline{}$ for more than two seconds.

Changing the display language

- 1. In Idle mode, press the Menu soft key.
- 2. Select Phone settings → Language.
- 3. Select a language.

Making a call

- 1. In Idle mode, enter the area code and phone number, and press \square
- 2. When you want to end the call, press 👨.

4 Answering a call

- 1. When the phone rings, press the Accept soft key or \square to answer a call. To reject the call, press the Reject soft key or 6.
- 2. When you want to end the call, press &

Adjusting the volume

- 1. In Idle mode, press the Menu soft key.
- 2. Select Sound settings → Ring volume.
- 3. Press Up or Down to adjust the volume level.
- 4. Press the OK soft key.

While a call is in progress, press the Volume keys to adjust the earpiece

Changing a ringtone for calls

- 1. In Idle mode, press the Menu soft key.
- 2. Select Sound settings → Ring tone.
- 3. Select a ringtone.

W Redialling recent numbers

- 1. In Idle mode, press 🔼.
- 2. Press Up or Down to scroll to the number you want.
- 3. Press 🔁 to dial the number.

Using the menus

In Idle mode, press the Menu soft key to enter the main menu.

Labels at the bottom corners of the display show the current soft key functions. Press the left soft key (i) or right soft key () to perform the function indicated.



without changing the

Use the 4-way navigation keys () as shortcuts to access your favourite menus. Up is fixed as a shortcut to

- 1. In Idle mode, press the Mo nu soft kev.
- 2. Select Select a key.
- 4. Select a menu to be assigned to the key.

If the selected menu contains additional submenus, repeat this step.

soft key or 🕪 .

1. In Idle mode, press the Menu soft key.

pressing the Navigation keys. Press the

4. Press the Navigation keys to find the setting of your choice.

the submenu

You can quickly access the menu you want by using shortcut numbers. The shortcut number displays in front of the menu name in Menu mode.

Select soft key or wi to confirm your chosen setting.

2. Press the Navigation keys to reach a desired menu and then press the

lect soft key or (*/i) to enter

3. If the menu contains any submenus, locate the one you want by

Menu map

1. SIM AT*

2. Call records

- 2.1 Missed calls
- 2.2 Received calls
- 2.3 Dialled calls
- 2.4 Delete all 2.5 Call time
- 2.6 Call cost*

- 3.1 Call diverting
- 3.2 Call barring
- 3.3 Call waiting
- 3.4 Network selection
- 3.5 Caller ID
- 3.6 Closed user group 3.7 Band selection

- 4.1 Ring tone
- 4.2 Ring volume 4.3 Alert type
- 4.4 Keypad tone
- 4.5 Message tone 4.6 Alert on call
- 4.7 Folder tone
- 4.8 Power on/off 4.9 Extra tones
- 5.1 Text messages
- 5.2 Multimedia messages
- 5.3 Push messages

- 6.1 WAP browser
- 6.2 Games
- 6.3 Sounds
- 6.4 Images 6.5 Delete all
- 6.6 Memory status

- 7.1 Alarm
- 7.2 Calendar 7.3 Time & Date
- 7.4 Calculator 7.5 To do list
- 7.6 Voice memo
- 8. FM Radio
- 9.1 Infrared activate

7.7 Currency exchange

- 9.2 Display settings
- 9.3 Greeting message 9.4 Own number
- 9.5 Language
- 9.6 Security
- 9.7 Extra settings
- 9.8 Short cut
- 9.9 Reset settings

soft kev Press the in Idle mode.

- 1 Search
- 2 New entry 3 Group search
- 4 Edit group 5 Speed dial
- 6 Delete all 7 Memory status 8 SDN*
- * Show only if supported by your SIM

4 Entering text

Changing the text input mode

In a text input field, press the right soft key until the input mode indicator you want appears:

- T9: T9 mode
- A : ABC mode
- 1 : Number mode
- · None: Symbol mode

T9 mode

1. Press 2 to 9 to start entering a word. Press each key once for one

Example: To enter "Hello" in T9 mode, press 4, 3, 5, 5, and 6.

T9 predicts the word that you are typing, and it may change with each key that you press.

- 2. Enter the whole word before editing or deleting characters.
- 3. When the word displays correctly, go to step 4. Otherwise, press 0 to display alternative word choices for the keys that you have pressed.
- 4. Press # to insert a space and enter the next word.

Feature	Description	Select	
Delete recent calls	Delete the call logs in each call type, or all logs at once.	Menu > Call records > Delete all	
Call time display	View the duration of recent calls you have dialled and received. Also reset the time counter.	Menu > Call records > Call time	
Call cost display	View the cost of your calls.	Menu > Call records > Call cost	
Network services	Access network services offered by your service provider.	Menu > Network services	
Select ringtone and volume	Select a ringtone for incoming calls, or a volume level.	Menu > Sound settings > Ring tone or Ring volume	
Alert type	Select an alert type for the call ringer.	Menu > Sound settings > Alert type	
Select key tone	Select a tone which the phone sounds when you press a key.	Menu > Sound settings > Keypad tone	
Select message tone	Select the alert ringtone for incoming SMS, MMS, and broadcast messages, or set how open you are informed of a new message.	Menu > Sound settings > Message tone	
Alert on call	Set the phone to alert you when you receive a new message or when the time for an alarm comes during a call.	Menu > Sound settings > Alert on call	

Feature	Description	Select
Greeting message	Enter the greeting message to be displayed when the phone is switched on.	Menu > Phone settings > Greeting message
Check your own phone numbers	Check your phone numbers or assign a name to them.	Menu > Phone settings > Own number
Display language	Select a language to be used for the display text.	Menu > Phone settings > Language
Security	Protect the phone against unauthorised use.	Menu > Phone settings > Security
Extra settings	Set the automatic redialling feature or the answering method.	Menu > Phone settings > Extra settings
Menu shortcuts	Set the Navigation keys as shortcuts to access your favourite menus directly.	Menu > Phone settings > Short cut
Reset the phone	Reset the phone to the factory default settings.	Menu > Phone settings > Reset settings

4 Important safety precautions

Read these guidelines before using your wireless phone. Failure to comply with them may be dangerous or illegal.

Do not use a hand-held phone while driving; park the vehicle first.

Press the keys labelled with the character you want:

- once for the first character
- twice for the second character
- and so on.

For example, press 2 three times to enter "C" and 5 two times to enter

Number mode

Press the keys corresponding to the digits you want.

Symbol mode

Press the number keys corresponding to the symbol you want and press the OK soft key. You can press Up or Down to display more symbols.

Tips for entering text

- To move the cursor, press the Navigation keys.
- To delete characters one by one, press C. To clear the display, press and hold C.
- To insert a space between characters, press #.
- To change case in T9 mode or ABC mode, press *.
- To enter punctuation marks in T9 mode or ABC mode, press 1.

	Feature	Description	Select
	Folder tone	Select the tone that the phone sounds when you open or close the phone.	Menu > Sound settings > Folder tone
	Power on/ off tone	Select the melody that the phone sounds when it is switched on or off.	Menu > Sound settings > Power on/ off
	Extra tones	Set additional tones for the phone.	Menu > Sound settings > Extra tones
	Read SMS or MMS messages	Read received, sent, or saved messages.	Menu > Messages > Text messages or Multimedia messages > Inbox, Outbox, or Draft
	Send SMS or MMS messages	Create and send messages to other mobile phones.	Menu > Messages > Text messages or Multimedia messages > Write new
	Message templates	Preset templates of frequently used messages or emoticons.	Menu > Messages > Text messages or Multimedia messages > Templates or Emoticon templates
	Messaging options	Set options for using messaging services.	Menu > Messages > Text messages or Multimedia messages > Settings or Setup

Do not use the phone at a refuelling point (service station) or near fuels or chemicals.

Wireless phones can cause interference. Using them in an aircraft is both illegal and dangerous.

Hospitals and health care facilities may be using equipment that could be sensitive to external RF energy. Follow any regulations or rules in force.

All wireless phones may be subject to interference, which could affect their performance.

Follow any special regulations in force in any area and always switch off your phone whenever it is forbidden to use it.

Your phone is not water-resistant. Keep it dry.

Use only in the normal position (held to the ear). Avoid unnecessary contact with the antenna when the phone is switched on

Key in the emergency number for your present location, then press $\boxed{\ }$. Do not end the call until given permission to do so.

Keep the phone and all its parts including accessories out of reach of small children.

4 Sending an SMS message

- 1. In Idle mode, press the Menu soft key.
- 2. Select Messages → Text messages → Write new.
- 3. Enter the message text.
- 4. Press the Options soft key and add items using the following options:
 - Add objects: add sounds, images, or animated images
- Add templates: add text templates.
- Add emoticon: add emoticons.
- Add phonebook: add Phonebook contacts.
- Add bookmark: add bookmark items.
- 5. Press the Options and select Send only, Save and send, or Save
- 6. If you select Save and send or Save only, select a memory location.
- 7. Enter a destination number and press the OK soft key.

4 Quick feature reference

This section provides brief explanations of features on your phone.

Feature	Description	Select
Find a contact	Search for contacts in Phonebook.	Phonebook > Search
Add a new contact	Add a new contact to Phonebook.	Phonebook > New entry
Search group	Search for Phonebook contacts in caller groups.	Phonebook > Group search
Change properties of a caller group	Select a ringtone for incoming calls and messages from members of a group. Also change the group name.	Phonebook > Edit group
Speed dial	Assign speed dial numbers (2 to 9) for eight of your most frequently dialled numbers.	Phonebook > Speed dial
Delete Phonebook contacts	Delete all Phonebook contacts stored in the phone's memory, on the SIM card, or both.	Phonebook > Delete all
Phonebook memory status	View the total number of Phonebook contacts in the phone's memory or on the SIM card.	Phonebook > Memory status
View recent calls	View the most recent calls you have dialled, received, or missed.	Menu > Call records > Missed calls, Received calls, Dialled calls

Description	Select		Feature	Description	Select
Delete messages in each message box, or all messages at once.	Menu > Messages > Text messages or Multimedia messages		Funbox memory status	Check the amount of memory in use for games, sounds and images.	Menu > Funbox > Memory status
Check memory information for	> Delete all Menu > Messages		Alarm	Set an alarm to sound at a specific time.	Menu > Organiser > Alarm
messages.	> Text messages or Multimedia messages	Calendar	Keep track of daily or monthly schedules.	Menu > Organiser > Calendar	
Access your voicemail server and	> Memory status Menu > Messages > Text messages > Voice mail Menu > Messages > Text messages > Text messages > Broadcast		Time and date	Set the current time and date manually.	Menu > Organiser > Time & Date
listen to messages on the network.			Calculator	Perform basic arithmetic functions.	Menu > Organiser > Calculator
Change settings for the service and access broadcast messages.			Task list	Create a list of tasks and assign a deadline to each task.	Menu > Organiser > To do list
Select or configure a connection profile to be used for MMS.	Menu > Messages > Multimedia messages > MMS profile	Voice memo	Record voice memos and listen them.	Menu > Organiser > Voice memo	
prome to be asea for times		Currency converter	Do currency conversions.	Menu > Organiser > Currency exchange	
Change the settings for the service, and access or delete push messages.	Menu > Messages > Push messages	FM rad	FM radio	Listen to music or news via the FM radio on your phone. You must connect the supplied headset to	Menu > FM Radio
Launch and configure the web browser.	Menu > Funbox > WAP browser		IrDA	the phone. Send and receive data to or from	Menu > Phone
Access games, sounds, images in your phone's memory.	Menu > Funbox > Games, Sounds,			IrDA-compatible computers or phones through the infrared port.	settings > Infrared activate
, ,	Images,		Display settings	Change settings for the display and backlight.	Menu > Phone settings > Display
Delete games, sounds, images in each media box, or all media files at once.	Menu > Funbox > Delete all		Securitys	and backlight.	settings > Display

Use only Samson-approved batteries and accessories, such as headsets and PC data cables. Use of any unauthorised accessories could damage you and your phone and may be dangerous.



Delete messages

Message

Voicemail

Broadcast

message MMS profile

Push message

Web browser

Access media

Delete all

media files

status

Risk of explosion if a battery is replaced by an incorrect type. Dispose used batteries according to the instructions.



At very high volume, prolonged listening to a headset can damage your hearing.

Only qualified service personnel may repair your phone.

SAR information

Your wireless phone is a radio transmitter and receiver. It is designed and manufactured not to exceed the emission limits for exposure to radio frequency (RF) energy set by the European Union (EU) Council. These limits are part of comprehensive guidelines and establish permitted levels of RF energy for the general population. The guidelines are based on the safety standards that were developed by independent scientific organisations through periodic and through evaluation of scientific studies.

The standards include a substantial safety margin designed to assure the safety of all persons, regardless of age and health.

The exposure standard for wireless phones employs a unit of measurement known as Specific Absorption Rate (SAR). The SAR limit set by the EU Council is 2.0 W/kg. The highest SAR value for this model phone was 0.475W/kg.

Declaration of Conformity (R&TTE)

Model description: Portable Celluar Telephone (GSM 900/1800/1900)

Model name: SGH-X210

Manufactured at: Samsung Electronics Co., Ltd, 94-1, Imsoo-Dong, Gumi City, Kyung-Buk,

to which this declaration relates, is in conformity with the following standards and/or other normative documents.

Safety : EN 60950-1:2001 : EN 50360:2001 SAR : EN 301 489-01 v1.4.1 (08-2002) EN 50361:200 : EN 301 489-07 v1.2.1 (08-2002) Network: EN 301 511 v9.0.2 (03-2003)

We hereby declare that [all essential radio test suites have been carried out and that] the above named product is in conformity to all the essential requirements of Directive 1999/5/

The conformity assessment procedure referred to in Article 10 and detailed in Annex[IV] of Directive 1999/5/EC has been followed with the involvement of the following Notified

BABT, Balfour House, Churchfield Road, Walton-on-Thames, Surrey, KT12 2TD, UK dentification mark: 0168

The technical documentation kept at:

Samsung Electronics QA Lab.

which will be made available upon request. (Representative in the EU)

Place and date of issue:

Samsung Electronics Euro OA Lab. Blackbushe Business Park, Saxony Way, Yateley, Hampshire, GU46 6GG, UK

D. C. palez Yong-Sang Park/S.Manage

CE0168

* It is not the address of Samsung Service Centre. For the address or the phone number of Samsung Service Centre, see the warranty card or contact the retailer where you purchased your phone.